

FRONT

BACK

80mm

70mm

Knightsbridge

These instructions should be read carefully and retained after installation by the end-user for future reference and maintenance.

These instructions should be used to aid the installation for the following products: NETPIRxxx, NETTS1xx, NET2xxxx, NET12xxxx

SAFETY

- This product must be installed in accordance with the latest edition of the IEE Wiring Regulations (BS7671) and current Building Regulations. If in any doubt, consult a qualified electrician.
- Please isolate the mains prior to installation or maintenance.
- Check the total load on the circuit (including when this product is fitted) does not exceed the rating of the circuit cable, fuse or circuit breaker.


- Please note the IP (Ingress Protection) rating of this product then deciding the location for installation
- Do not overload this accessory or subject it to conditions outside its rating.
- This product is for indoor use only.
- This product is IP20 rated.

INSTALLATION

- Always ensure the wall surface is flat and smooth.
- When using Class I accessories, all earth connections must be made and maintained. Use green/yellow sleeving on earth conductors that are not insulated.
- Check all electrical connections are secure with all exposed copper within the terminal and no loose strands of cable.
- Fit the unit into a suitable modular frame and wall box taking care not to compress, damage or trap any cables. If using metal mounting boxes with four lugs, remove or bend fully back the unnecessary ones.
- Connect to the mains supply ensuring the correct polarity is observed by following the relevant wiring diagram

1.


NETPIRXXX



PIR Switch Module

L (LIVE)= red or brown
N (NEUTRAL)= black or blue
⊕ (EARTH)= green and yellow

NETTS1xx




Touchless Switch Module

L (LIVE)= red or brown
N (NEUTRAL)= black or blue
⊕ (EARTH)= green and yellow

2.


NET2xxx or NET12xxx

1G 2-way modular



L OUT-1 L OUT-2

1G intermediate modular



L OUT-1 L OUT-2

3.

- Switch on and check for correct operation.

160mm

WARNING

Products with USB and LED or Neon indicators must be disconnected from the circuit if subjected to any high voltage or insulation resistance testing. Irreparable damage will occur if this instruction is not followed. Please note this kind of damage will void the warranty.

WARRANTY

This product has a warranty of 25 years (2 years on electronic products) from date of purchase. Failure to install this product in accordance with the current edition of the IEE Wiring Regulations (BS7671), improper use, or removal of the batch code will invalidate the warranty. If this product should fail within its warranty period, it should be returned to the place of purchase for a free of charge replacement. ML Accessories does not accept responsibility for any installation costs associated with the replacement product. Your statutory rights are not affected. ML Accessories reserve the right to alter product specification without prior notice.

4.

Manufacturers Declaration of Conformity For ML Accessories (Knightsbridge)

Electrical products in accordance with UKCA marking
ML Accessories Ltd. declare that all products have been designed, manufactured, and tested in accordance with the requirements of the relevant legislation

UKCA marking legislation
UK SI 2016 No. 1091 Electro Magnetic Compatibility Regulations 2016
UK SI 2016 No. 1101 The Electrical Equipment (Safety) Regulations 2016
UK SI 2012 No. 3052 Restriction of the use of Certain Hazardous Substances in Electrical and Electronic Equipment Regulations 2012

UK SI 2017 No. 1206 Radio Equipment regulations 2017
UK SI 2021 No. 1095 The Ecodesign for Energy-Related Products and Energy Information (Lighting Products) Regulations 2021

Included Legislation
UK SI 2008 No. 2852 UK REACH
UK SI 2013 No. 3113 WEEE

Safety Standards
Full individual declarations and specific safety standards applicable to relevant product series can be found on our website: www.mlaccessories.co.uk

We hereby declare that the equipment named above has been designed to comply with the relevant sections of the above referenced specifications. The products comply with all essential requirements of the directives.

Catherine Connolly
CEO

Lee Saunders
Technical Assessment & Compliance Manager

ML Accessories Ltd. Unit E Chiltern Park, Boscombe Road, Dunstable, Bedfordshire, LU5 4LT
This declaration becomes invalid if technical or operational modifications are introduced without ML Accessories Ltd. written consent.

Knightsbridge



5.

Manufacturers Declaration of Conformity For ML Accessories (Knightsbridge)

Electrical products in accordance with CE marking
ML Accessories Ltd. Declare that all products have been designed, manufactured, and tested in accordance with the requirements of the relevant legislation

CE marking legislation
In accordance with the following Directives:
2014/35/EU Low Voltage Directive
2014/30/EU EMC Directive
2014/53/EU Radio Equipment Directive

Including Legislation
1907/2006 REACH
2015/863 RoHS
2021/341 ERP

Safety Standards
Full individual declarations and specific safety standards applicable to relevant product series can be found on our website: www.mlaccessories.co.uk

We hereby declare that the equipment named above has been designed to comply with the relevant sections of the above referenced specifications. The product complies with all essential requirements of the directives.

Catherine Connolly
CEO

Lee Saunders
Technical Assessment & Compliance Manager

ML Accessories Ltd. Unit E Chiltern Park, Boscombe Road, Dunstable, Bedfordshire, LU5 4LT
This declaration becomes invalid if technical or operational modifications are introduced without ML Accessories Ltd. written consent.

6.



SUPPLIED BY:
**(UK) MANUFACTURER
ML ACCESSORIES LTD,
UNIT E CHILTERN PARK,
BOSCOMBE ROAD, DUNSTABLE LU5 4LT,
WWW.MLACCESSORIES.CO.UK
(EU) AUTHORISED REPRESENTATIVE
SLV LIGHTING GROUP,
DAIMLERSTRASSE 21-23,
52531 ÜBACH-PALENBERG, GERMANY
EMAIL: EPREL@GROUP.SLV.COM
MADE IN CHINA**

BTDEC23_V1



7.

140mm