

Data Sheet Product Code: XFC71D



## Product Description: 2-Gang (10A Intermediate Switch + 10A 1- or

 $\bigcirc$  1 x 1- or 2-way switch with 1 x intermediate (3-way) switch alongside

O Suitable for controlling both mains and low voltage lighting

- Ø Intermediate switch enables 3-way switching
- Ø Contemporary, ultra-slim faceplate

**Product Features** 



Barcode: 5021575211436

2-Way Rocker Switch)

Finish: Polished Chrome

Product Category: Intermediate Rocker Switch

Insert/Knob Colour: Chrome Rockers

Range: Ultraflat

Faceplate Depth: 1mm

Net Weight: 146g

Gross Weight: 148g

Fixing Centres: 60.3mm

Depth from Mounting Face: 18.5mm

Recommended Back Box Depth: 25mm

Operating Voltage: 230v 50Hz

Maximum Load Rating: 10A

Maximum Current Rating: 10A

Terminal (Live) Diameter: 3.3mm; Capacity: 3 x 1.5mm<sup>2</sup>

Terminal (Earth) Diameter: 3.3mm; Capacity: 3 x 1.5mm<sup>2</sup>

Intended Applications: Indoor Use Only. Domestic lighting circuits.

Safety Advice: Product Must Be Earthed.

Applicable Safety Standard: BS EN 60669-1

Commodity Code: 85365007

10 YEAR GUARANTEE BF



Declaration of Conformity

All information is subject to change without notice. Errors and omissions excepted. Images are for illustrative purposes only. Individual features and colours may vary. Refer to date of issue to identify latest version.

Date of Issue: 06th February 2022 © Doyle & Tratt Products Ltd, Carylls Lea, Faygate, West Sussex, RH12 4SJ, United Kingdom. All rights reserved.