



# Data Sheet

Product Code: XR5TUB

*This product is made to order*

**Product Description:** 2-Gang 13A Single Pole WiFi Switched Socket for Smart Life

**Range:** Classic

**Finish:** Pewter

**Product Category:** Smart Sockets

**Insert/Knob Colour:** Black Insert

**Barcode:** 5021575010336

**Dimensions:** 91x150x31mm

**Faceplate Depth:** 8mm

**Net Weight:** 219g

**Gross Weight:** 222g

**Fixing Centres:** 120.6mm

**Depth from Mounting Face:** 16.9mm

**Recommended Back Box Depth:** 25mm

**Operating Voltage:** 230v 50Hz

**Maximum Load Rating:** 13A

**Maximum Current Rating:** 13A

**Terminal (Live) Diameter:** 4.8mm; **Capacity:** 4 x 2.5mm<sup>2</sup>

**Terminal (Neutral) Diameter:** 4.8mm; **Capacity:** 4 x 2.5mm<sup>2</sup>

**Terminal (Earth) Diameter:** 4.8mm; **Capacity:** 4 x 2.5mm<sup>2</sup>

**Intended Applications:** Indoor Use Only. Domestic power supply.

**Safety Advice:** Product Must Be Earthed.

**Applicable Safety Standard:** BS 1363-2

**Commodity Code:** 85366990



**10 YEAR GUARANTEE**

**BRITISH MADE** 

## Product Features

- ✔ Smart Socket for the Tuya/Smartlife app, downloadable from the Apple App Store or Google Play
- ✔ No need to reach behind furniture to switch sockets on or off
- ✔ Turn lamps or appliances on and off remotely or on a timer
- ✔ Use scheduling to save energy or simulate occupancy
- ✔ No hub or subscription required

Declaration of Conformity

*All information is subject to change without notice. Errors and omissions excepted. Images are for illustrative purposes only. Individual features and colours may vary. Refer to date of issue to identify latest version.*

*Date of Issue: 23rd April 2024 © Doyle & Tratt Products Ltd, Carylls Lea, Faygate, West Sussex, RH12 4SJ, United Kingdom. All rights reserved.*